

## Setting up a Belkin Router on your Bluebox Broadband Connection

Thank you for choosing Bluebox.

Now that you have decided to go wireless with your connection the first step is connecting to your routers wireless network using the wireless key supplied with the router. Following this please connect the LAN cable from our POE adaptor directly to the Modem port on the back of your wireless router.

Following this, in your browser, type "http://router" (you do not need to type in anything else such as "www"). Then press the Enter key.

If you're still having trouble running the manual setup option, type "192.168.2.1" in your browser (you do not need to type in anything else such as "http://" or "www"). Then press the Enter key.

You will be presented with the following screen:

<ul> <li>A ttp://192.168.2.</li> </ul>	ם, ע	- = C X [ 5etup H	ome ×		
🏠 🕶 🔯 👻 📾 💌 Pa	ge 💌 Safety 💌 Tools 💌 🔞	- 😃 🕹 🔊 🛞 🕒			
BELKIN   Router Setup	uter Setup Router Setup Utäty		Home   Help   Login	(1) Click Login	
LAN Setup LAN Setings DHCP Clent List	Status	English Expañol Français	Deutsch Nederlands Italiano	× 100 2000	
Internet WAN Connection Type DNS MAC Address Wireless Channel and SSID	Version Info Firmware Version Boot Version Hardware Serial No.	FSD8236- 4_WW_3.00.04 1.00 FSD8236-4 v3000 20025823604796	LAN Settings LANWLAN MAC IP address Subnet mask DHCP Server	94:44:52:50:e1:f4 192.168.2.1 255.255.255.0 Enabled	
Security WI-FI Protected Setup Use as Access Point MAC Address Control Firewall	Internet Settings WAN MAC address Connection Type Subnet mask Wan IP Default externer	94:44:52:50:e1:f5 Dynamic	Festures Firewall Settings SSID Security WPS Brenote	Enabled Belkin_N_Wireless_50e1f4 Enabled Enabled	
Virtual Servers Client IP Filters IMAC Address Filtering DINS UDNS WAN Ping Blocking Security Log	Default gateway DNS Address		Memote Management UPNP	Disabled Enabled	
Utilities Restart Router					



Once you login you will see the following screen:



The next stage in the setup is clicking on "Connection Type" on the left hand side of the screen and you will be presented with the following screen, click Static then Next.





You will then be presented with the following screen:

(-) - (2 - (2 - (2 - (2 - (2 - (2 - (2 -	92168.21 was slat hter 9 • Page • Safety • Tools •	P-≣CX ■ 5.0 × 0	wan>	Connection	а Туре х Ж		
BELKIN	Router Setup						
L <b>AS Sctup</b> LAS Settings DRCP Chent Lint	WAN > Connection T To enter your Static IP setting:	ype > Static IF	ation bein	ow and click	*Apply chan	ges". More leto	
nternet WAN	IP Address >		ЭE				(6) Enter the details
NS IAC Address	Subnet Mask >		1C			1 4	as shown below
ireless ternel and SSE	ISP Gateway Address >	e file Callings		10	3(		
		Dear Changes		Apply Ch	anpes	1	(7) Click Apply Changes
irewall Phan Servers Sant IF Filten KAC Address Filtering INZ CRIS KAM Ping Blacking							L

On this screen enter in the following information:

IP ADDRESS	172. XXX . XXX . XXX
SUBNET MASK	255.255.255.252
DEFAULT GATEWAY	172. XXX . XXX. XXX

Details marked 'X' can be found on your Engineer receipt, by emailing <u>broadband@nwewireless.com</u> or by calling 02871351 999



You will be presented with the following screen:

🗲 🔿 🙋 http://19	216821/wan_stat.cgi	
BELKIN	▼ Page ▼ Safety ▼ Tools ▼ ♥ ▼ & ↓> ↓ ♥ ♥ S Router Setup	
LAN Setup LAN Setings DRCP Cleat List	WAN > DNS If your ISP provided you with a specific DNS address to use, enter the address in this window and	
Internet WAN Connection Type	click "Apply Changes".	(8) Enter Details
MAC Address	DNS Address >	as below
Wretess Charvel and SSD Security Use as Access Point MAC Address Control Ficewall Virtual Servers Client # Piters	Secondary DNS Address > b	(9) Click Apply Changes
MAC Address Filtering		

Enter the following DNS addresses:

## DNS ADDRESS 78.155.251.1

## SECONDARY DNS ADDRESS 78.155.250.1

When the countdown finishes the router should have applied the connection settings successfully. Please note that here at Bluebox we take no responsibility for a customer's wireless security. Please seek advice from your router documentation in setting up this feature. After configuring your wireless security settings you should close down the router setup screen.

At this point please ensure you are correctly connected to your wireless network so that you can enjoy your Bluebox connection wirelessly.

If you are unable to browse the internet following this setup then please do not hesitate to contact our support helpline on 02871 351999 or if you wish to do so send us an email at <u>broadband@nwewireless.com</u> and one of our technical representatives will reply shortly following the receipt of your email.